ABUS Security-Center

SE1100

Flush mount key–switch

Use the flush mount key–switch to arm and disarm your alarm system. Simply turn the key instead of entering a PIN code. Operating your system is faster and easier.

Apart from the arm/disarm function of the alarm system (or individual partitions), you can use flush mount the key–switch to control electronic equipment (entrance lighting, garage door, etc.). Two switch contacts are provided. You can set these as a permanent contact or as a pulse generator.

The two coloured LEDs inform you permanently about the state of connected devices. For example, you can see if the system is currently armed or disarmed. The reinforced fascia plate, the high–quality ABUS cylinder and a robust weatherproof housing (IP 55) protect the key–switch against external influences.
The flush mount key–switch is designed for half–cylinders (10/30). It is available for both surface and flush fitting. The surface–fitted variant is protected from tampering by a cover contact and an anti–removal wall contact.

Product highlights:

- High security – cannot be removed illegally
- Simple activating and deactivating
- For flush fitting
- Tamper–monitored

SE1100

Flush mount key–switch

Technical Data	
Protection type	IP55
Contacts	3, switchable
Maximum contact capacity	500mA, 30V DC
Tamper protection	Wall/ceiling contact
Removal protection	Yes
LED	2, for status display
Voltage supply LED	10–15V DC
Power consumption per LED	max. 2mA
Dimensions	134 x 106 x 42 mm
Weight	450g